



# AJAX

## Tech specs

### MotionProtect Curtain

<b>Classification</b>	Radio-interlinked photoelectric security detector
<b>Type of detector</b>	Wireless
<b>Installation method</b>	Indoors only
<b>Compatibility</b>	Operates with all Ajax Hubs and Range Extenders
<b>Sensing element</b>	Two PIR sensors
<b>Alarm signal delivery time</b>	0.15 s
<b>Motion detection distance</b>	Adjustable (from 6 to 15 meters)
<b>False alarm reduction</b>	Available, Correlation Signal Processing
<b>Sensitivity</b>	Adjustable, 3 levels
<b>Detection angles</b>	Horizontally – 6° Vertically – 90°
<b>Time for motion detection</b>	From 0.3 to 2 m/s
<b>Recommended installation height</b>	2.4 meters
<b>Power supply</b>	Battery: CR123A, 3 V
<b>Battery life</b>	Up to 3 years



## Tech specs

# MotionProtect Curtain

### Jeweller radio technology

Communication range with detectors – up to 1,700 m in an open space  
Two-way communication between devices

Radio frequency bands (depends on the region of sale):

866.0 – 866.5 MHz

868.0 – 868.6 MHz

868.7 – 869.2 MHz

905.0 – 926.5 MHz

915.85 – 926.5 MHz

921.0 – 922.0 MHz

Self-adjusting RF output power – up to 20 mW

Block encryption based on AES algorithm

Detector polling period – 12–300 s

Frequency hopping

### Protection class

IP54

### Temperature sensor

Available

### Operating temperature range

From -10°C to +40°C

### Operating humidity

Up to 95%

### Anti-sabotage

Fraud protection  
Jamming notification  
Tamper-resistant

### Remote setting and testing

+

### Dimensions

134 × 44 × 34 mm

### Weight

118 g

### Warranty

Replacement and repair within 24 months of the date of sale. The warranty does not cover batteries.

Tech specs

## MotionProtect Curtain

### Complete set

MotionProtect Curtain motion detector  
SmartBracket mounting panel  
CR123A batteries (pre-installed)  
Bracket  
Installation kit  
User's guide

